

There is a Better Way



# WHY UPGRADE WITH EMIUM'S EXIT & EMERGENCY LIGHTS?

Designed and built for commercial use to facilitate a smooth, cost-effective transition into the cutting-edge performance and quality of LED lighting.

Emium LED exit and emergency lights provide a clean and modern look with slim profile.

Fixtures are equipped for use in new construction, remodels, or for easily retrofitting older lighting technology.

This series' internal solid-state transfer switch automatically connects the internal battery to LED lamp heads for minimum 90-minute emergency illumination.

## **FEATURES**

- Reduce energy consumption and operating costs by 80% or more.
- Meets UL924, NFPA 101 Life Safety Code, NEC, OSHA, Local and State Codes.
- UL Listed for damp locations (0°C 50°C).
- Charge rate/power "ON" LED indicator light and push to test switch for mandated code compliance testing.
- Injection-molded, engineering grade, 5VA flame retardant, high-impact resistant, thermoplastic in white.
- 24 Hour recharge period.
- Estimated 50,000-hour LED Lifespan.

#### **Recommended Use:**

- · Commercial buildings
- Hotels
- Offices
- Retail stores
- Plazas



There is a Better Way

# **LED Exit Signs & Emergency Lights**

Standard Series





## **Exit Sign**

- Red Lettering
- 120-277VAC
- 4.8V Rechargeable NiCd Battery

#### Mounting

- Ceiling Mount
- Wall mount

types are included

Both mounting



# **Exit Sign & Light Pipe**


- 4.5W Light Pipe
- Red Lettering
- 120-277VAC
- 4.8V Rechargeable NiCd Battery

### **Mounting**

- Ceiling Mount
- Wall mount

Both mounting types are included

EL-04-PIPE-IRW-RC





# Exit Sign & Emergency Light

- 1.5W Emergency Light
- Red Lettering
- 120-277VAC
- 4.8V Rechargeable NiCd Battery

### **Mounting**

- Ceiling Mount
- Both mounting
- Wall mount

types are included

EL-04-CRW-LED-RC-HL



# **Emergency Light**

- 1W per head: 2 watts total
- 120-277VAC
- 3.6V Rechargeable NiCd Battery

#### **Mounting**

- Ceiling Mount Wall mount
- Both mounting types are
- included

EL-04-EL1-LED

